### **Features**

### Line **Inductors**

- Tested and proved in RECOM filter design
- RoHS2+ compliant
- **SMD**




### **RLS-186**

# **Inductors Power Supply**

# Line for **RECOM**

**Model Numbering** 




#### Notes:

Note1: with suffix "-R", standard packaging tape and reel without suffix optional airbag packaging


#### Specifications (measured @ Ta= 25°C, unless otherwise stated)

BASIC CHARACTERISTICS				
Parameter		Condition	Value	
Inductance	L	100kHz/250V	18μH ±10%	
DC Resistance	RDC	@ 25°C	100mΩ max.	
Rated Current	I <sub>B</sub>	$\Delta T \le 40^{\circ}C$	1.89A max.	
Saturation Current	sat	I ΔL/LI < 10%	2.14A typ.	

#### Inductance vs. Current graph



#### Impedance graph













## **RLS-186**

#### Specifications (measured @ Ta= 25°C, unless otherwise stated)

ENVIRONMENTAL				
Parameter	Condition	Value		
Operating Temperature Range	with derating	-40°C to +105°C		
Operating Humidity	non-condensing	95% RH max.		







# **RLS-186**

#### Specifications (measured @ Ta= 25°C, unless otherwise stated)

PACKAGING INFORMATION				
Parameter	Туре	Value		
Declaring Dimension / MANAD	tape and reel (carton)	355.0 x 340.0 x 35.0mm		
Packaging Dimension (LxWxH)	airbag	120.0 x 100.0 x 30.0mm		
Dealessing Overtite	tape and reel	1000pcs		
Packaging Quantity	airbag	50pcs		
Tape Width		16.0mm		
Storage Temperature Range		-55°C to +125°C		
Storage Humidity	non-condensing	95% RH max.		

The product information and specifications may be subject to changes even without prior written notice. The product has been designed for various applications; its suitability lies in the responsibility of each customer. The products are not authorized for use in safety-critical applications without RECOM's explicit written consent. A safety-critical application is an application where a failure may reasonably be expected to endanger or cause loss of life, inflict bodily harm or damage property. The applicant shall indemnify and hold harmless RECOM, its affiliated companies and its representatives against any damage claims in connection with the unauthorized use of RECOM products in such safety-critical applications.

www.recom-power.com REV.: 2/2024 P-3